



## Merchant Bulkhead Installation Guide

**Product codes:** 09712, 09303, 09605

---

### INSTRUCTIONS FOR USE AND INSTALLATION

### GENERAL INFORMATION & TECHNICAL SPECIFICATIONS

#### PRODUCTS MANUFACTURED IN EU

- 230V ~ 50Hz
- Class I
- E27 porcelain lamp holder
- Not intended for mesh connection.
- Intended for connection to fixed wiring.
- Double-insulation 3G1.5 power cable should be used for the connection of the light fixture.
- Power cable not included.

#### GENERAL INFORMATION ABOUT SAFETY

- Before any work turn off the mains supply.
- Installation should only be carried out by a qualified electrician, who should be aware of the current Regulations on Internal & External Installations.
- In case of glass breakage, replace immediately.
- Lightbulb Wattage should never exceed the Wattage (W) indicated on the label or the packaging of the light fixture.
- The product should be connected to a line protected by a differential current circuit, while the nominal persistent operating current should not exceed 30mA (leakage relay).

#### Included in the package:

1 Light fixture

Address: Navigator Lighting (part of Lampfix) Unit 6 Fen End, Stotfold, Hitchin, Herts. SG5 4BA

Tel: 01462 731173 | Email: [sales@navigatorlighting.co.uk](mailto:sales@navigatorlighting.co.uk) | Website: [navigatorlighting.co.uk](http://navigatorlighting.co.uk)

V1 20.10.2025



- 1 plastic insulating cover for the lamp holder
- 2 sets of wall-plugs and screws
- 2 rubber retainers
- 2 plastic washers
- 3 insulating hoses

## **LIGHT FIXTURE INSTALLATION**

### **A. FIXING THE LIGHT FIXTURE ON A MOUNTING SURFACE**

- Unscrew the cage and remove the glass from the body of the light fixture.
- Using the body of the light fixture as an installation guide, mark the surface on which you wish to mount it.
- Drill holes on the mounting surface and fasten the body of the light fixture to it, using the supplied wall-plugs and screws. To ensure the insulation of the light fixture, use the plastic washers and rubber retainers when screwing the screws.

### **B. CONNECTING THE POWER CABLE**

- Pass the cable through the cable clamp.
- Cover the wires with the supplied insulating hoses.
- Connect the line (brown) and neutral (blue) wires to the lamp holder and the grounding wire (yellow) to the body of the light fixture next to the grounding symbol  $\perp$ , using the supplied screw and M4 washer.
- Place the plastic insulating cover under the lamp holder.
- Screw the lamp to the lamp holder.
- Fit the glass and fasten the cage to the body of the light fixture.
- Turn on the power supply.

### **C. REPLACING THE LIGHTBULB**

- Turn off the mains supply.
- Do not try to replace the lightbulb unless it has completely cooled down as it may cause serious burns on the skin.
- Open the lightbulb's cover.
- Twist and pull the lightbulb gently.
- Do not touch the lightbulb with bare hands.
- Always use clean protective gloves when handling a lightbulb.
- Use a clean towel to clean the lightbulb in case you touch it accidentally.

Address: Navigator Lighting (part of Lampfix) Unit 6 Fen End, Stotfold, Hitchin, Herts. SG5 4BA



# Navigator

- When replacing the lightbulb, twist it very carefully while it is still in the lamp holder.
- Before feeding again with power, replace the lightbulb's cover to maintain the impermeability of the fixture.

**The manufacturer bears no responsibility for any injury or damage resulting from incorrect installation or use of the product**

Address: Navigator Lighting (part of Lampfix) Unit 6 Fen End, Stotfold, Hitchin, Herts. SG5 4BA

Tel: 01462 731173 | Email: [sales@navigatorlighting.co.uk](mailto:sales@navigatorlighting.co.uk) | Website: [navigatorlighting.co.uk](http://navigatorlighting.co.uk)

V1 20.10.2025